

Code	Photo Control	Time Clock	Remote Switch	Timed Override	Sweep Sequence	Key Applications	Priority
1	•					<b>Exterior-Photo</b> (security lighting)	▶ Photo control
2		•				<b>Exterior-Time</b> (canopy lighting)	▶ Time clock
3	•	•				<b>Exterior-Photo/Time</b> (signage lighting)	▶ Photo control or time clock
6		•	•			<b>Interior HID-Time</b> (gymnasiums, warehouses, aircraft hangers lighting)	▶ Time clock
7	•	•	•			<b>Interior HID-Photo</b> (skylit atriums, retail stores, warehouses)	▶ Remote switch initiates start of photo control and time clock ▶ Remote switch has priority when photo control is ON only
9	•		•	•		<b>Exterior-Photo w/ Maintenance Timed Override</b> (enhanced security lighting)	▶ Photo control ▶ Remote switch starts timed override when photo control is OFF
14		•	•	•	•	<b>Interior-Time w/ Timed Override &amp; Sweep Sequence</b> (standard offices, schools lighting)	▶ Time clock ▶ Remote switch starts timed override w/ sweep sequence when time clock is OFF
15	•	•	•	•	•	<b>Interior-Photo/Time w/ Timed Override &amp; Sweep Sequence</b> (daylighting in offices, schools)	▶ Remote switch initiates start of photo control and time clock sequence ▶ Remote switch has priority when photo control and time clock is ON ▶ Remote switch starts timed override w/ sweep sequence when time clock is OFF