



Power Tap

LODESTAR Accessory



PROJECT _____

LOCATION _____

FEATURES

- Taps power to provide constant AC power
- Eliminates special wiring
- Does not interfere with normal phototcontrol operation
- 7-Pin model allows pass thru communication

DESCRIPTION

The Power Tap Adapter works with any luminaire that utilizes a photocontrol and locking type receptacle. It installs between the photocontrol and the twist-lock receptacle.

TECHNICAL DATA

Voltage/Current	120-480 VAC, 10 Amps AC continuous.
Current	10 Amps AC continuous
Housing	UV stabilized impact resistant gray polypropylene
Cable Type	SOOW 16/2
Base	High-temperature ABS
Blades	Solid brass, three prong locking type
Gasket	Cross linked polyethylene
Packaging	Individual units are sealed in water resistant plastic

ORDERING INFORMATION

Product	Description
TLA-PT-3P	3 Pin Power Tap
TLA-PT-7P	7 Pin Power Tap

Standard cable length is 48". Custom cable lengths and other configurations may be available, please consult the factory.

